

Lighthouse Canopy Conversion Kit

Product Datasheet

- ✓ UNIQUE AND EXCLUSIVE DESIGN
- ✓ Compatible with the Lighthouse range of Floodlights
- ✓ Suitable for retrofitting
- ✓ Significant energy savings and low pay back time!



Product Description

The Lighthouse canopy conversion kit houses our energy saving 50, 80 or 100 watt flood lights. This can be retrospectively fitted into an existing canopy to replace standard metal halide fittings. It creates a crisp, modern visual appearance. This conversion offers significant annual energy savings further enhanced by the possibility of wiring to a PIR.

Designed for ease of installation the kit should take around 25 minutes to fit.

Dimensions: 760mm x 760mm and fabricated from 5mm foam PVC complete with aluminium support bars and supplied with fixings.

Energy Saving

Watts	UK	NI	EIRE	Average LUX
50w	£896	£1,224	€ 1,224	175
80w	£752	£1,064	€ 1,064	260
100w	£692	£952	€ 952	300

Based on 8 lights used for 4,000 hours charges at 12p, 17p and 17c.
Prices in comparison to 250 w MH/ SON.
Assumes standard canopy height Of 4.4m

Compatible Floodlights

Data/Product	FL50	FL80	FL100
Part Number	FL50	FL80	FL100
Power (w)	50	80	100
Colour Temperature	4000k	4000k	4000k
Lumen Output	4100	6500	8000
Current	225ma	365ma	450ma
Lighting Distance	20m	25m	30m
Alternative to	150w MH/SON	250w MH/SON	250w MH/SON



Lighthouse
energy saving lighting

1
YEAR
WARRANTY